

CLS DMX 4000 Digital Dimmer

The CLS DMX 4000 is a new dimmer from CLS with lots of new features, relieving the extremely popular DMX4 from its hard work during the last decade.

Main features:

- Set a fader on your mixing console to max. Then press the memory button on the DMX4000 for 5 sec. This will store the selected channel as the DMX Start address. No difficult dipswitch settings.
- Set the next fader to max will set the dimmers max value 10% down.
- Set the third fader to max will change all the channels to be a switchpack.
- Easy mounting on the truss/stands/wall etc. together with the lamps.

Specifications:

- The CLS DMX4000 is a 4 Channel DMX digital dimmer.
- 4x1000W - Total max load: 16A
- Noiseless
- The CLS Easystore (1 button operation):
Selecting the start address from 512 DMX channels
Dimmer/switchpack mode
10% Down for use of 4x1000W lamps on 16A mains outlet
- Led for power
- Led for DMX signals
- Led for 10% down
- Led for Switch pack selection
- XLR 5 pin DMX in/out by Neutriks
- No circuit breakers to change
- Power outlets by 4 schuko contacts
- 220-240V 50Hz
- Ultra Compact Dimension: 190 x 120 x 75 mm
- Weight: 2 kg

